

C1-mini-C is an LED spotlight for installation on a magnetic track, that is controlled by the Casambi App, and suitable for showcase lighting in museum and retail settings. It is 360° rotatable, 90° swivelling and available with a variety of optics, 5 color temperatures and 3 standard finishes.


TECHNICAL DATA

Wattage / Input	2.5W (12VDC)
Power Supply	Remote - See Magnetic Track Sheet
Dimming	Individually controlled by the Casambi App 810 steps (flicker-free) from 100% to 0.4%.
Construction	Body: Anodized Aluminum
CCT	2700K, 3000K, 3500K, 4000K, 5700K
CRI	>90
Delivered Lumens	160 lm (2.5W, 3000K, 30°)
Efficacy	64 lm/W (2.5W, 3000K, 30°)
Optics	9 Standard, See Below
Finishes	3 Standard, See Below
Fixture Dimensions	Ø0.65" x 1.65" h
Lumen Maintenance	L80,B10 >50,000hrs
IP Rating	IP20

NOTE: Track to be ordered separately



Fixture Dimensions



ORDERING INFORMATION

Example: C1-MINI-C-25-40-18-G. Accessories / Power Supplies ordered separately.

C1-MINI-C	-	25	-		-		-	
Model No.	Wattage	CCT	Optics	Finish				
C1-MINI-C	25 - 2.5W	27 - 2700K	08 - 8°	B - Anodized Black				
		30 - 3000K	15 - 15°	S - Silver				
		35 - 3500K	18 - 18°	G - Gold				
		40 - 4000K	26 - 26°	C - Custom RAL				
		57 - 5700K	30 - 30°	(consult factory for "C")				
			45 - 45°					
			80 - 80°					
			47 - 47°+25°					
			40 - 40°+10°					

Job Name/Date:

Fixture Type Designation:

ACCESSORIES - OPTIONAL



Honeycomb Grid




Anti-Glare Tube



Inclined Tube



Snoot (8°)



Light Diffusion Foil



Barn Door



Zoom Optic (9°-33°)

See separate sheet
for Magnetic Track.
Consult factory for
Remote Power
Supply for Magnetic
Track.

DIMMING




The C1-mini-C spotlight is controlled via the Casambi app. The set value is automatically saved and retained even after a power cut. The dimming range has 810 steps (flicker-free) from 100% to 0.4%. The dimming frequency is 19.75 kHz. The Casambi app can be freely downloaded from the App Store or Google Play. After opening, the app automatically finds all Casambi-operated spotlights. Tap on Add All luminaires to ... / My network. All spotlights are connected into a network and the Luminaires menu opens automatically. (To switch on or off - tap the symbol; to dim - swipe horizontally over the symbol)



CASAMBI

PHOTOMETRIC DATA

for light color 3000 K | standard lens 30° | color rendering index typ. 97, R9 > 90, R12 > 90 | color variation ≤ 3 SDCM



Job Name/Date:

Fixture Type Designation: