

MAXI QUAD 1.1 - 1.2 - 1.3

Installation instructions



WARNING!!!

Please read the following instructions carefully.

IMPORTANT:




- Although LED runs on a very low voltage, always cut off the power supply before installing the LED light or subjecting it to maintenance.
- Unauthorised alterations or tampering of the product will invalidate all the conditions of guarantee.
- This fixture must be installed by a qualified electrician.
- Designplan Lighting is not responsible if its fixtures are not installed in according to local safety standards.
- Data contained in this document may be changed at any moment without prior notice.

ELECTRICAL CONNECTIONS:

- LED lights run at constant current.
- As for the choice of the power supplies, please consider the tension through which they are fed and the max power consumption of LEDs you have to install.
- **The system must be fed only if all the spots are connected.**
- The power supplies must be installed in aerated rooms, far from heat sources. A situation of overworking or a lack of air circulation will not permit a natural dissipation.


NOTES:

- Under no circumstance must this product be covered by thermal-insulating material or similar.




MAXI QUAD 1.1 - 1.2 - 1.3

Installation instructions



	B	X	S	H min
1.1	□2.95"	1.97"min	.47"	5.90"
1.2	2.95"x5.71"	1.97"min	.47"	5.90"
1.3	2.95"x8.46"	1.97"min	.47"	5.90"




POWER CONSUMPTION	6 W; 12 W; 18 W		
TOTAL POWER CONSUMPTION	8 W; 14.5 W; 22 W	(Tc 85°C) TYPICAL LED LUMINOUS FLUX	510 lm
SUPPLY VOLTAGE	500mA	(Tc 85°C) LED EFFICIENCY	80 lm/W
CONNECTION	series connection.	LIGHTING EFFICIENCY	58 lm/W
N° AND TYPE OF LED USED	1/2/3 power LED Cree XM-L	FINISHING	Aluminium white finishing
AVERAGE LED LIFE	75% after 50.000 hours	FIXING	Recessed with springs
LED COLOURS AVAILABLE	White: 2700K; 3000K; 4000K;	APPLIANCE CLASS	Class 2
CRI	80 ÷ 85	WEIGHT	0.6 / 0.9 / 1.2 kg
OPERATING TEMPERATURE	0°C ÷ +45°C	PHOTOBIOLOGICAL SAFETY	

MAXI QUAD 1.1 - 1.2 - 1.3

Installation instructions




1



REMOTE CLASS 2
POWER SUPPLY
500mA

2



3

